

171PR75

1

10/069487  
JC19 Rec'd PCT/PTO 27 FEB 2002

## SPECIFICATION

### TITLE OF THE INVENTION

Optical amplifier apparatus

5

### TECHNICAL FIELD

The present invention relates to an optical amplifier apparatus. More particularly, this invention relates to the optical amplifier apparatus which is utilized for an optical repeater and others for wavelength multiplex transmission.

10

### BACKGROUND ART

In recent years, along the rapid increase in demand for communications using the Internet and the like, there have been actively progressed researches and developments into and practical application of large-capacity and high-speed transmission systems in networks. As one of such signal transmission systems, a wavelength multiplex transmission system for transmitting signals by multiplexing signal lights of a plurality of mutually different wavelengths through one transmission fiber has been known. According to signal transmission based on the wavelength multiplex transmission system, it is possible to transmit information for each signal of each wavelength,

20

25

and this system is suitable for large-capacity transmission. An optical fiber amplifier (an optical amplifier) constructed of a rare-earth-added optical fiber has the following characteristics, and is suitable for application to wavelength multiplex transmission. The amplifier does not depend on a transmission speed, the amplifier can simplify repeaters, and the amplifier collectively amplifies all input signal lights.

However, the optical amplifier has gain wavelength dependency, and it has been known that there occurs a variance between wavelengths in the light output or the gain of each wavelength after the amplification. Therefore, there occurs a variance between wavelengths in the optical power after the transmission. Particularly, when carrying out a multi-stage repeating by the optical amplifier, the variance between wavelengths due to the optical amplifier at each repeating stage is accumulated. This brings about the inconvenience that the variance between wavelengths of the optical power after the transmission becomes larger.

As an example of an optical amplifier gain equalization technique for solving the above problem, there is a technique (an optical equalization amplifier) as disclosed in Japanese Patent Application Laid-open No. 9-211507. This optical equalization amplifier is an apparatus for equalizing the output levels of a plurality of wavelength components as

well as making constant the light input and output levels,  
in the amplification of wavelength-multiplexed lights. As  
shown in Fig. 17, the optical equalization amplifier has  
an optical amplifier 103 and a variable optical attenuator  
5 104 arranged between an input terminal 101 and an output  
terminal 102.

The optical amplifier 103 has such gain inclination  
characteristics, that a gain at a long wavelength side  
becomes smaller when the excitation ratio is high, and that  
10 a gain at a short wavelength side becomes smaller when the  
excitation ratio is low. In other words, the optical  
amplifier 103 has a negative inclination of gain relative  
to wavelength when the excitation ratio is high, and has  
a positive inclination of gain relative to wavelength when  
15 the excitation ratio is low. As an example of a means which  
changes the excitation ratio, there are an excitation power  
control unit, and an optical level control unit for  
controlling a signal light that is input to the amplifier.

In the above optical amplifier apparatus, an input  
20 wavelength-multiplexed signal is amplified by the optical  
amplifier 103. A level of each wavelength is detected at  
the output side of the optical amplifier 103. The optical  
amplifier apparatus controls the excitation power (gain  
control) of the optical amplifier 103 so that the levels  
25 (gains) of the wavelengths are equalized. An output level

is detected at the output side of the variable optical attenuator 104. The optical amplifier apparatus controls (output control) the attenuation of the output signal light of the variable optical attenuator 104.

5           However, a transmission line and a passive device have wavelength dependency attenuation, and therefore, optical signals of different levels are received at the input of the optical amplifier. This brings about a variance in the optical levels between the wavelengths. A variance of  
10   optical levels generated by one optical amplifier is small. However, as dozens to hundreds of optical amplifiers are provided for long-distance transmission like a submarine cable that connects between continents, the accumulation of such variances results in a small optical level in a channel  
15   of a specific signal wavelength. This has a risk of deteriorating an optical signal to noise ratio.

          As the wavelength signal of the lowest power among the multiplexed wavelengths becomes a lower limit of reception power after the transmission, a maximum  
20   transmission distance is limited by the wavelength signal of the lowest power. Therefore, it is important to lower the variance between wavelengths after the transmission, in order to expand the maximum repetition transmission distance. For minimizing the variance in the optical signal  
25   to noise ratio between channels after the transmission and

minimizing the variance in the reception characteristics, there is a technique of providing a gain inclination at the transmission side in advance (pre-emphasizing). An inline automatic gain inclination compensator may be inserted into  
5 the transmission line.

However, the provision of a large pre-emphasis lowers an optical SNR, and this also distorts a signal waveform due to a nonlinear effect of the transmission line attributable to the rise in signal optical power of a distance  
10 average. The pre-emphasis has inconvenience that the pre-emphasis effect becomes smaller as the transmission distance becomes longer. On the other hand, the inline automatic gain inclination compensator can minimize excessive deterioration of the optical SNR and the reception  
15 characteristics. However, there are other problems like the reliability of this compensator and the increase in the cost of the apparatus.

It is an object of this invention to provide an optical amplifier apparatus capable of controlling a gain  
20 inclination and making constant a light output level in amplifying wavelength-multiplexed lights, without depending on the provision of pre-emphasis and without generating other problems like the reliability of a compensator and the increase in the cost of the apparatus.

## DISCLOSURE OF THE INVENTION

The optical amplifier apparatus according to one aspect of the present invention comprises an optical amplifier which amplifies an input signal light, an output  
5 detecting unit which detects an output level of the optical amplifier, an output control unit which controls an output level of the optical amplifier according to an output level detected by the output detecting unit, a gain inclination  
detecting unit which detects a gain inclination relating  
10 to a wavelength of the optical amplifier, and a gain inclination control unit which controls a gain inclination of the optical amplifier according to a gain inclination detected by the gain inclination detecting unit.

The optical amplifier apparatus according to another  
15 aspect of the present invention comprises an optical amplifier which amplifies an input wavelength-multiplexed signal light, an optical variable attenuator which attenuates an output signal light of the optical amplifier,  
an output detecting unit which detects an output level at  
20 an output side of the optical variable attenuator, an output control unit which controls the attenuation of an output signal light attenuated by the optical variable attenuator according to an output level detected by the output detecting  
unit, a gain inclination detecting unit which detects a gain  
25 inclination relating to a wavelength of the optical amplifier,

and a gain inclination control unit which controls a gain inclination by adjusting an output light of an excitation light source of the optical amplifier according to a gain inclination detected by the gain inclination detecting unit.

5       The optical amplifier apparatus according to still another aspect of the present invention comprises an optical amplifier which amplifies an input wavelength-multiplexed signal light, an optical variable attenuator which attenuates an output signal light of the optical amplifier,  
10   an output detecting unit which detects an output level at an output side of the optical variable attenuator, an output control unit which controls an output light of an excitation light source of the optical amplifier according to an output level detected by the output detecting unit, a gain  
15   inclination detecting unit which detects a gain inclination relating to a wavelength of the optical amplifier, and a gain inclination control unit which controls a gain inclination by adjusting the attenuation of an output signal light attenuated by the optical variable attenuator  
20   according to a gain inclination detected by the gain inclination detecting unit.

      The optical amplifier apparatus according to still another aspect of the present invention comprises an optical amplifier which amplifies an input wavelength-multiplexed  
25   signal light, a compensation light source which injects a

compensation light that propagates in a forward direction of a propagation direction of an input signal light to the optical amplifier, a wavelength selecting unit which interrupts a compensation light at an output side of the optical amplifier, and transmits only a signal light, an output detecting unit which detects an output level of a signal light at an output side of the wavelength selecting unit, an output control unit which controls an output light of the compensation light source according to an output level detected by the output detecting unit, a gain inclination detecting unit which detects a gain inclination of the optical amplifier, and a gain inclination control unit which controls a gain inclination by adjusting an output light of an excitation light source of the optical amplifier according to a gain inclination detected by the gain inclination detecting unit.

The optical amplifier apparatus according to still another aspect of the present invention comprises an optical amplifier which amplifies an input wavelength-multiplexed signal light, a compensation light source which injects a compensation light that propagates in a forward direction of a propagation direction of the input signal light to the optical amplifier, a wavelength selecting unit which interrupts a compensation light at an output side of the optical amplifier, and transmits only a signal light, an



output detecting unit which detects an output level of a  
signal light at an output side of the wavelength selecting  
unit, an output control unit which controls an output light  
of an excitation light source of the optical amplifier  
5 according to an output level detected by the output detecting  
unit, a gain inclination detecting unit which detects a gain  
inclination of the optical amplifier, and a gain inclination  
control unit which controls a gain inclination by adjusting  
an output light of the compensation light source according  
10 to a gain inclination detected by the gain inclination  
detecting unit.

The optical amplifier apparatus according to still  
another aspect of the present invention comprises an optical  
amplifier which amplifies an input wavelength-multiplexed  
15 signal light, a compensation light source which injects a  
compensation light that propagates in a forward direction  
of a propagation direction of the input signal light to the  
optical amplifier, an optical variable attenuator which  
attenuates an output signal light of the optical amplifier,  
20 a wavelength selecting unit which interrupts a compensation  
light at an output side of the optical variable attenuator,  
and transmits only a signal light, an output detecting unit  
which detects an output level of a signal light at an output  
side of the wavelength selecting unit, an output control  
25 unit which controls the attenuation of an output signal light

of the optical variable attenuator according to an output level detected by the output detecting unit, a gain inclination detecting unit which detects a gain inclination of the optical amplifier, and a gain inclination control unit which controls a gain inclination by adjusting an output light of the compensation light source according to a gain inclination detected by the gain inclination detecting unit.

The optical amplifier apparatus according to still another aspect of the present invention comprises an optical amplifier which amplifies an input wavelength-multiplexed signal light, a compensation light source which injects a compensation light that propagates in a forward direction of a propagation direction of the input signal light to the optical amplifier, an optical variable attenuator which attenuates an output signal light of the optical amplifier, a wavelength selecting unit which interrupts a compensation light at an output side of the optical variable attenuator, and transmits only a signal light, an output detecting unit which detects an output level of a signal light at an output side of the wavelength selecting unit, an output control unit which controls an output light of the compensation light source according to an output level detected by the output detecting unit, a gain inclination detecting unit which detects a gain inclination of the optical amplifier, and a gain inclination control unit which controls a gain

inclination by adjusting the attenuation of an output signal light attenuated by the optical variable attenuator according to a gain inclination detected by the gain inclination detecting unit.

5       The optical amplifier apparatus according to still another aspect of the present invention comprises a first optical amplifier which amplifies an input wavelength-multiplexed signal light, an optical variable attenuator which attenuates an output signal light of the  
10 first optical amplifier, a second optical amplifier which amplifies an output signal light of the optical variable attenuator, an output detecting unit which detects an output level at an output side of the second optical amplifier, an output control unit which controls the attenuation of  
15 an output signal light attenuated by the optical variable attenuator according to an output level detected by the output detecting unit, a gain inclination detecting unit which detects a gain inclination of the second optical amplifier, and a gain inclination control unit which controls  
20 a gain inclination by adjusting output lights of excitation light sources of the first optical amplifier and the second optical amplifier according to a gain inclination detected by the gain inclination detecting unit.

      The optical amplifier apparatus according to still  
25 another aspect of the present invention comprises a first

optical amplifier which amplifies an input wavelength-multiplexed signal light, an optical variable attenuator which attenuates an output signal light of the first optical amplifier, a second optical amplifier which  
5 amplifies an output signal light of the optical variable attenuator, an output detecting unit which detects an output level at an output side of the second optical amplifier, an output control unit which controls output lights of excitation light sources of the first optical amplifier and  
10 the second optical amplifier according to an output level detected by the output detecting unit, a gain inclination detecting unit which detects a gain inclination of the second optical amplifier, and a gain inclination control unit which controls a gain inclination by adjusting the attenuation  
15 of an output signal light attenuated by the optical variable attenuator according to a gain inclination detected by the gain inclination detecting unit.

The optical amplifier apparatus according to still another aspect of the present invention comprises an optical  
20 amplifier which amplifies an input wavelength-multiplexed signal light, a compensation light source which injects a compensation light that propagates in a forward direction of a propagation direction of the input signal light to the optical amplifier, a first optical amplifier which amplifies  
25 the signal light, an optical variable attenuator which

attenuates an output signal light of the first optical amplifier, a second optical amplifier which amplifies an output signal light of the optical variable attenuator, a wavelength selecting unit which interrupts a compensation light at an output side of the second optical amplifier, and transmits only a signal light, an output detecting unit which detects an output level of a signal light at an output side of the wavelength selecting unit, an output control unit which controls the attenuation of an output signal light attenuated by the optical variable attenuator according to an output level detected by the output detecting unit, a gain inclination detecting unit which detects a gain inclination of the second optical amplifier, and a gain inclination control unit which controls a gain inclination by adjusting an output light of the compensation light source according to a gain inclination detected by the gain inclination detecting unit.

The optical amplifier apparatus according to still another aspect of the present invention comprises an optical amplifier which amplifies an input wavelength-multiplexed signal light, a compensation light source which injects a compensation light that propagates in a forward direction of a propagation direction of the input signal light to the optical amplifier, a first optical amplifier which amplifies the signal light, an optical variable attenuator which

attenuates an output signal light of the first optical amplifier, a second optical amplifier which amplifies an output signal light of the optical variable attenuator, a wavelength selecting unit which interrupts a compensation light at an output side of the second optical amplifier, and transmits only a signal light, an output detecting unit which detects an output level of a signal light at an output side of the wavelength selecting unit, an output control unit which controls an output light of the compensation light source according to an output level detected by the output detecting unit, a gain inclination detecting unit which detects a gain inclination of the second optical amplifier, and a gain inclination control unit which controls a gain inclination by adjusting the attenuation of an output signal light attenuated by the optical variable attenuator according to a gain inclination detected by the gain inclination detecting unit.

The optical amplifier apparatus according to still another aspect of the present invention comprises an optical amplifier which amplifies an input wavelength-multiplexed signal light, a compensation light source which injects a compensation light that propagates in a forward direction of a propagation direction of the input signal light to the optical amplifier, a first optical amplifier which amplifies the signal light, a second optical amplifier which amplifies

an output signal light of the first optical amplifier, a wavelength selecting unit which interrupts a compensation light at an output side of the second optical amplifier, and transmits only a signal light, an output detecting unit  
5 which detects an output level of a signal light at an output side of the wavelength selecting unit, an output control unit which controls output lights of excitation light sources of the first optical amplifier and the second optical amplifier according to an output level detected by the output  
10 detecting unit, a gain inclination detecting unit which detects a gain inclination of the optical amplifier, and a gain inclination control unit which controls a gain inclination by adjusting an output light of the compensation light source according to a gain inclination detected by  
15 the gain inclination detecting unit.

The optical amplifier apparatus according to still another aspect of the present invention comprises an optical amplifier which amplifies an input wavelength-multiplexed signal light in an excitation light source, a compensation  
20 light source which injects a compensation light that propagates in a forward direction of a propagation direction of the input signal light to the optical amplifier, a first optical amplifier which amplifies the signal light, a second optical amplifier which amplifies an output signal light  
25 of the first optical amplifier, a wavelength selecting unit

which interrupts a compensation light at an output side of the second optical amplifier, and transmits only a signal light, an output detecting unit which detects an output level of a signal light at an output side of the wavelength selecting unit, an output control unit which controls an output light of the compensation light source according to an output level detected by the output detecting unit, a gain inclination detecting unit which detects a gain inclination of the second optical amplifier, and a gain inclination control unit which controls a gain inclination by adjusting output lights of an excitation light source of the first optical amplifier and an excitation light source of the second optical amplifier according to a gain inclination detected by the gain inclination detecting unit.

15           In the above-mentioned optical amplifier apparatus, the gain inclination detecting unit branches a wavelength-multiplexed signal light, and detects a gain inclination from optical signal levels of a shortest wave and a longest wave.

20           In the above-mentioned optical amplifier apparatus, the gain inclination detecting unit branches a wavelength-multiplexed signal light, and detects a gain inclination from optical signal levels of three or more waves.

25           In the above-mentioned optical amplifier apparatus,



the optical amplifier apparatus inputs a wavelength-multiplexed signal light having mutually different frequency components superimposed on optical signals of a shortest wave and a longest wave respectively, and the gain inclination detecting unit detects frequency components superimposed on the optical signals of respective wavelengths thereby to detect a gain inclination.

In the above-mentioned optical amplifier apparatus, the optical amplifier apparatus inputs a wavelength-multiplexed signal light having mutually different frequency components superimposed on optical signals of three or more waves respectively, and the gain inclination detecting unit detects frequency components superimposed on the optical signals thereby to detect a gain inclination.

#### BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a diagram showing a structure of a first embodiment of an optical amplifier apparatus according to the present invention; Fig. 2 is a graph showing an example of a gain inclination control of the optical amplifier apparatus according to the first embodiment; Fig. 3 is a diagram showing a structure of one example of a gain inclination detecting unit in an optical amplifier apparatus according to the present invention; Fig. 4 is a diagram

showing a structure of another example of a gain inclination detecting unit in an optical amplifier apparatus according to the present invention; Fig. 5 is a diagram showing a structure of a second embodiment of an optical amplifier apparatus according to the present invention; Fig. 6 is a diagram showing a structure of a third embodiment of an optical amplifier apparatus according to the present invention; Fig. 7 is a diagram showing a structure of a fourth embodiment of an optical amplifier apparatus according to the present invention; Fig. 8 is a diagram showing a structure of a fifth embodiment of an optical amplifier apparatus according to the present invention; Fig. 9 is a diagram showing a structure of a sixth embodiment of an optical amplifier apparatus according to the present invention; Fig. 10 is a diagram showing a structure of a seventh embodiment of an optical amplifier apparatus according to the present invention; Fig. 11 is a graph showing an example of a gain inclination control of the optical amplifier apparatus according to the seventh embodiment; Fig. 12 is a diagram showing a structure of an eighth embodiment of an optical amplifier apparatus according to the present invention; Fig. 13 is a diagram showing a structure of a ninth embodiment of an optical amplifier apparatus according to the present invention; Fig. 14 is a diagram showing a structure of a tenth embodiment of an optical amplifier apparatus according

to the present invention; Fig. 15 is a diagram showing a structure of an eleventh embodiment of an optical amplifier apparatus according to the present invention; Fig. 16 is a diagram showing a structure of a twelfth embodiment of an optical amplifier apparatus according to the present invention; and Fig. 17 is a diagram showing an example of a conventional structure of an optical amplifier apparatus.

#### BEST MODE FOR CARRYING OUT THE INVENTION

Embodiments of an optical amplifier apparatus according to the present invention will be explained in detail below with reference to the attached drawings.

##### First Embodiment:

Fig. 1 shows a first embodiment of an optical amplifier apparatus according to the present invention. In Fig. 1, a reference numeral 1 denotes an input terminal, a reference numeral 2 denotes an output terminal, a reference numeral 3 denotes an optical amplifier, a reference numeral 4 denotes an optical variable attenuator, a reference numeral 5 denotes an output detecting unit, a reference numeral 6 denotes an output control unit, a reference numeral 7 denotes a gain inclination detecting unit, and a reference numeral 8 denotes a gain inclination control unit.

The optical amplifier apparatus of the first embodiment has the optical amplifier 3, the optical variable

attenuator 4, the output detecting unit 5, the output control unit 6, the gain inclination detecting unit 7, and the gain inclination control unit 8. The optical amplifier 3 amplifies a wavelength-multiplexed signal light that is  
5 input to the input terminal 1 connected with a not shown optical fiber.

The optical variable attenuator 4 variably attenuates an output signal light of the optical amplifier 3. Such an optical variable attenuator can be realized by, for  
10 example, a Faraday rotor that utilizes a magneto-optic effect. It is also possible to structure this optical variable attenuator 4 with a device utilizing an electrooptic effect of  $\text{LiNbO}_3$  or an acoustooptical effect.

The output detecting unit 5 detects an output level  
15 of the optical variable attenuator 4, and outputs the detected value of the output level to the output control unit 6. The output control unit 6 controls the attenuation of an output signal light attenuated by the optical variable attenuator 4 according to the detection value, so that an  
20 output level detected by the output detecting unit 5 becomes constant.

The gain inclination detecting unit 7 detects a gain inclination from an output of the optical variable attenuator 4, and outputs this detection value to the gain inclination  
25 control unit 8. The gain inclination control unit 8 adjusts

an excitation light of the optical amplifier 3 according to a gain inclination (a detection value) that is detected by the gain inclination detecting unit 7.

Fig. 2 shows an example of a gain inclination control.

5 In this gain inclination control, the control is carried out by setting an input level of the optical amplifier 3 to -8dBm, an output level of the optical variable attenuator 4 to +1dBm, and a gain G of the optical amplifier 3 to 9, 11, and 13 dB respectively. It can be understood from this  
10 that the gain inclination is controlled by controlling only the gain G of the optical amplifier 3. Based on the above control, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the  
15 amplification of a wavelength-multiplexed signal light.

A detailed example of the gain inclination detecting unit 7 will be explained next with reference to Fig. 3. This gain inclination detecting unit 7 is for branching a wavelength-multiplexed signal light, and detecting a gain  
20 inclination from optical signal levels of a shortest wavelength  $\lambda_1$  and a longest wavelength  $\lambda_n$ . The wavelength selecting unit 9 divides only the components of the shortest wavelength  $\lambda_1$  and the longest wavelength  $\lambda_n$  out of a wavelength-multiplexed signal light that is output from the  
25 optical amplifier 3, more strictly, a

wavelength-multiplexed signal light output of the optical variable attenuator 4. The wavelength selecting unit 9 then sends the respective components to optical detecting units 10-1 and 10-n. It is possible to structure the wavelength selecting unit 9 with ease by using an optical filter. It is possible to use a photodiode, an avalanche photodiode, and a photocounter for the optical detecting units 10-1 and 10-n respectively.

The shortest wavelength  $\lambda_1$  is sent to the optical detecting unit 10-1, and the longest wavelength  $\lambda_n$  is sent to the optical detecting unit 10-n. The optical detecting units 10-1 and 10-n convert the received lights into electric signals respectively, and detect a level of the shortest wavelength  $\lambda_1$  and a level of the longest wavelength  $\lambda_n$  of the signal light respectively. The detection values are sent to a gain inclination detecting circuit 11. The gain inclination detecting circuit 11 can detect a gain inclination by comparing the level of the shortest wavelength  $\lambda_1$  with the level of the longest wavelength  $\lambda_n$ .

In this first embodiment, it is explained that the gain inclination is detected from the components of the shortest wavelength  $\lambda_1$  and the level of the longest wavelength  $\lambda_n$ . However, it is also possible to detect a gain inclination from optical signal levels of three or more waves. In this case, wavelength selecting units may be

inserted by a number of multiplexed wavelengths of a wavelength-multiplexed optical signal. These wavelength selecting units divide the signal light having the wavelengths  $\lambda_1, \lambda_2, \dots$ , and  $\lambda_n$  multiplexed together, and send  
5 wavelength signals of these wavelengths  $\lambda_1, \lambda_2, \dots$ , and  $\lambda_n$  to respective optical detecting units. Thereafter, the operation similar to that of the above embodiment is carried out.

It is also possible to arrange such that a transmitter  
10 side superimposes mutually different frequency components on the optical signals of the shortest wavelength  $\lambda_1$  and the longest wavelength  $\lambda_2$  respectively. Then, the frequency components superimposed on the optical signals of respective wavelengths may be detected to detect a gain inclination.  
15 When a low-frequency tone signal superimposing system is employed, it is possible to accurately control a gain without an influence of cumulative natural discharge optical noise. An example of a structure this gain inclination detecting unit 7 will be explained with reference to Fig. 4. The gain  
20 inclination detecting unit 7 is constructed of an optical detecting unit 10, band-pass filters (BPF's) 12-1 and 12-n, level detecting units 13-1 and 13-n, and a gain inclination detecting circuit 14.

A wavelength-multiplexed signal light output of an  
25 optical repeater is input to the optical detecting unit 10.

The band-pass filters 12-1 and 12-n extract respectively the frequency components allocated to wavelengths, from a detection signal. The level detecting units 13-1 and 13-n detect respectively the levels of signal lights of these  
5 frequency components.

In this case, the band-pass filter 12-1 extracts a frequency component  $f_1$  that has been superimposed on the shortest wavelength  $\lambda_1$ , and the band-pass filter 12-n extracts a frequency component  $f_n$  that has been superimposed  
10 on the longest wavelength  $\lambda_n$ . The level detecting units 13-1 and 13-n detect respectively the levels of the extracted frequency components  $f_1$  and  $f_n$ , and send the respective detection values to the gain inclination detecting circuit  
14. The gain inclination detecting circuit 14 detects a  
15 gain inclination by comparing the levels of these frequency components.

In this first embodiment, it is explained that the gain inclination is detected by superimposing mutually different frequency components on only the shortest  
20 wavelength and the longest wavelength. However, it is also possible to superimpose mutually different frequency components on optical signals of three or more waves. The gain inclination detecting circuit detects the superimposed frequency components thereby to detect a gain inclination.  
25 In this case, it is necessary to mutually differentiate the



wavelengths of the lights that are output from respective optical transmitters, and mutually differentiate the frequencies of sinusoidal wave signals that are superimposed. Further, band-pass filters and level detectors  
5 corresponding to the number of superimposed frequencies need to be prepared respectively for the gain inclination detecting unit 7. The center frequency of each band-pass filter is corresponded to the frequency of each sinusoidal wave signal that is superimposed.

10 Second Embodiment:

Fig. 5 shows a second embodiment of an optical amplifier apparatus according to the present invention. In Fig. 5, portions corresponding to those in Fig. 1 are attached with like reference numerals of the portions in Fig. 1, and their  
15 explanation will be omitted.

The optical amplifier apparatus of the second embodiment has the optical amplifier 3, the optical variable attenuator 4, the output detecting unit 5, an output control unit 15, the gain inclination detecting unit 7, and a gain  
20 inclination control unit 16.

The output control unit 15 controls an output light of an excitation light source of the optical amplifier 3 so that an output level becomes constant, according to an output level detected by the output detecting unit 5. The  
25 gain inclination control unit 16 controls a gain inclination

to an optimum value by adjusting the attenuation of an output signal light attenuated by the optical variable attenuator 4 according to a gain inclination detected by the gain inclination detecting unit 7.

5       Based on the above control, in this second embodiment also, like in the first embodiment, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of a  
10 wavelength-multiplexed signal light.

#### Third Embodiment:

Fig. 6 shows a third embodiment of an optical amplifier apparatus according to the present invention. In Fig. 6, portions corresponding to those in Fig. 1 are attached with  
15 like reference numerals of the portions in Fig. 1, and their explanation will be omitted.

The optical amplifier apparatus of the third embodiment has the optical amplifier 3, a compensation light source 17, a wavelength selecting unit 18, the output  
20 detecting unit 5, an output control unit 19, the gain inclination detecting unit 7, and the gain inclination control unit 8.

The compensation light source 17 injects to an input side of the optical amplifier 3 a compensation light that  
25 propagates in a forward direction of a propagation direction

of an input signal light to the optical amplifier 3. In this case, the gain of the optical amplifier 3 changes depending on total power of a signal light and a compensation light. Therefore, the power of the signal light changes  
5 depending on the power of the compensation light, and then the level of a wavelength-multiplexed signal light at an output terminal 2 changes. The wavelength selecting unit 18 is constructed of an optical rejection filter or a coupler, for example. This wavelength selecting unit 18 interrupts  
10 only a light of the wavelength of the compensation light source 17 (the compensation light) out of the output light of the optical amplifier 3, and transmits other components of the wavelength-multiplexed signal light.

The output detecting unit 5 detects an output level  
15 of a wavelength-multiplexed signal light at an output side of the wavelength selecting unit 18, and outputs a detection value to the output control unit 19. The output control unit 19 controls an output level of the compensation light source 17 according to the detection value so that the output  
20 level detected by the output detecting unit 5 becomes constant. The gain inclination detecting unit 7 detects a gain inclination from an output of the optical variable attenuator 4, and outputs a detection value to the gain inclination control unit 8. The gain inclination control  
25 unit 8 controls the gain inclination to an optimum value

by adjusting an excitation light of the optical amplifier 3 according to a gain inclination (a detection value) detected by the gain inclination detecting unit 7.

Therefore, in this third embodiment also, like in the first embodiment, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed signal light.

#### 10 Fourth Embodiment:

Fig. 7 shows a fourth embodiment of an optical amplifier apparatus according to the present invention. In Fig. 7, portions corresponding to those in Fig. 5 and Fig. 6 are attached with like reference numerals of the portions in Fig. 5 and Fig. 6, and their explanation will be omitted.

The optical amplifier apparatus of the fourth embodiment has the optical amplifier 3, the compensation light source 17, the wavelength selecting unit 18, the output detecting unit 5, the output control unit 15, the gain inclination detecting unit 7, and a gain inclination control unit 20.

The output detecting unit 5 detects an output level of a wavelength-multiplexed signal light at an output side of the wavelength selecting unit 18, and outputs a detection value to the output control unit 15. The output control

unit 15 controls an output light of an excitation light source of the optical amplifier 3 according to the detection value so that the output level detected by the output detecting unit 5 becomes constant. The gain inclination detecting unit 7 detects a gain inclination from an output of the optical variable attenuator 4, and outputs a detection value to the gain inclination control unit 20. The gain inclination control unit 20 controls the gain inclination to an optimum value by adjusting an output level of the compensation light source 17 according to a gain inclination (i.e. a value of the gain inclination) detected by the gain inclination detecting unit 7.

Therefore, in this fourth embodiment also, like in the first embodiment, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed signal light.

#### Fifth Embodiment:

Fig. 8 shows a fifth embodiment of an optical amplifier apparatus according to the present invention. In Fig. 8, portions corresponding to those in Fig. 1 and Fig. 7 are attached with like reference numerals of the portions in Fig. 1 and Fig. 7, and their explanation will be omitted.

The optical amplifier apparatus of the fifth

embodiment has the optical amplifier 3, the optical variable attenuator 4, the compensation light source 17, the wavelength selecting unit 18, the output detecting unit 5, the output control unit 6, the gain inclination detecting unit 7, and the gain inclination control unit 20.

The output detecting unit 5 detects an output level of a wavelength-multiplexed signal light at an output side of the wavelength selecting unit 18, and outputs a detection value to the output control unit 6. The output control unit 6 controls the attenuation of an output signal light of the optical variable attenuator 4 according to the detection value so that the output level detected by the output detecting unit 5 becomes constant. The gain inclination detecting unit 7 detects a gain inclination from an output of the optical variable attenuator 4, and outputs a detection value to the gain inclination control unit 20. The gain inclination control unit 20 controls the gain inclination to an optimum value by adjusting an output level of the compensation light source 17 according to a gain inclination (i.e. a value of the gain inclination) detected by the gain inclination detecting unit 7, in a similar manner to that of the fourth embodiment.

Therefore, in this fifth embodiment also, like in the first embodiment, it is possible to realize an optical amplifier apparatus capable of controlling the gain

inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed signal light.

Sixth Embodiment:

5           Fig. 9 shows a sixth embodiment of an optical amplifier apparatus according to the present invention. In Fig. 9, portions corresponding to those in Fig. 5 and Fig. 6 are attached with like reference numerals of the portions in Fig. 5 and Fig. 6, and their explanation will be omitted.

10           The optical amplifier apparatus of the sixth embodiment has the optical amplifier 3, the optical variable attenuator 4, the compensation light source 17, the wavelength selecting unit 18, the output detecting unit 5, the output control unit 19, the gain inclination detecting unit 7, and the gain inclination control unit 16.

          The output detecting unit 5 detects an output level of a wavelength-multiplexed signal light at an output side of the wavelength selecting unit 18, and outputs a detection value to the output control unit 19. The output control unit 19 controls an output level of the compensation light source 17 according to the detection value so that the output level detected by the output detecting unit 5 becomes constant, in a similar manner to that of the third embodiment. The gain inclination detecting unit 7 detects a gain inclination from an output of the optical variable attenuator

20           

25

4, and outputs a detection value to the gain inclination control unit 16. The gain inclination control unit 16 controls the gain inclination to an optimum value by adjusting the attenuation of an output signal light attenuated by the optical variable attenuator 4 according to a gain inclination detected by the gain inclination detecting unit 7, in a similar manner to that of the second embodiment.

Therefore, in this sixth embodiment also, like in the first embodiment, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed signal light.

Seventh Embodiment:

Fig. 10 shows a seventh embodiment of an optical amplifier apparatus according to the present invention. In Fig. 10, portions corresponding to those in Fig. 1 are attached with like reference numerals of the portions in Fig. 1, and their explanation will be omitted.

The optical amplifier apparatus of the seventh embodiment has the first and second optical amplifiers 3-1 and 3-2, the optical variable attenuator 4, output detecting units 5-1 and 5-2, the output control unit 6, the gain inclination detecting unit 7, a gain inclination control



unit 23, input detecting units 21-1 and 21-2, and gain control units 24-1 and 24-2.

The gain of the first optical amplifier 3-1 and the gain of the second optical amplifier 3-2 are always the same.

5 The output detecting unit 5-2 monitors an output level of the second optical amplifier 3-2, and the output control unit 6 control the optical variable attenuator 4 so that this output level becomes constant. Attenuation A of the optical variable attenuator 4 is uniquely determined as

10  $A = P_2 - P_1 - 2 \times G$ , where G represents a gain of the first optical amplifier 3-1 as well as a gain of the second optical amplifier 3-2, P-1 represents an input level of the first optical amplifier 3-1, and P2 represents an output level of the second optical amplifier 3-2. On the other hand, a gain inclination

15 D is expressed as a function of the gain G, like  $D = D(G)$ .

In other words, it is possible to uniquely determine the gain inclination D based on the gain G of the first optical amplifier 3-1 and the second optical amplifier 3-2. It is possible to control the gain inclination by giving only the

20 gain G of the optical amplifier from the outside, without changing the input and output levels.

Fig. 11 shows an example of a gain inclination control. In this example of the gain inclination control, the control is carried out by setting an input level P1 of the first

25 optical amplifier 3-1 to -8dBm, an output level P2 of the

second optical amplifier 3-2 to +3dBm, and the gain G of the optical amplifiers to 9, 11, and 13 dB respectively. It can be understood that the gain inclination is controlled by controlling only the gain G of the optical amplifiers.

5           Therefore, in this seventh embodiment also, like in the first embodiment, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed  
10 signal light.

Eighth Embodiment:

Fig. 12 shows an eighth embodiment of an optical amplifier apparatus according to the present invention. In Fig. 12, portions corresponding to those in Fig. 5 and Fig.  
15 10 are attached with like reference numerals of the portions in Fig. 5 and Fig. 10, and their explanation will be omitted.

The optical amplifier apparatus of the eighth embodiment has the first and second optical amplifiers 3-1 and 3-2, the optical variable attenuator 4, output detecting  
20 units 5-1 and 5-2, the output control unit 15, the gain inclination detecting unit 7, the gain inclination control unit 16, the input detecting units 21-1 and 21-2, and the gain control units 24-1 and 24-2.

The output control unit 15 controls output lights of  
25 excitation light sources of the first optical amplifier 3-1

and the second optical amplifier 3-2 so that an output level becomes constant according to an output level detected by the output detecting unit 5-2. In this case, the gain control unit 24-1 and the gain control unit 24-2 control the output  
5 lights of the excitation light sources so that the gain of the first optical amplifier 3-1 becomes equal to the gain of the second optical amplifier 3-2. The gain inclination control unit 16 controls the gain inclination to an optimum value by adjusting the attenuation of an output signal light  
10 attenuated by the optical variable attenuator 4 according to a gain inclination detected by the gain inclination detecting unit 7.

Therefore, in this eighth embodiment also, like in the first embodiment, it is possible to realize an optical  
15 amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed signal light.

#### Ninth Embodiment:

20 Fig. 13 shows a ninth embodiment of an optical amplifier apparatus according to the present invention.

The optical amplifier apparatus of the ninth embodiment has the first and second optical amplifiers 3-1 and 3-2, the optical variable attenuator 4, a first  
25 compensation light source 17-1, a second compensation light

source 17-2, a first wavelength selecting unit 18-1, a second wavelength selecting unit 18-2, output detecting units 5-1 and 5-2, the output control unit 6, the gain inclination detecting unit 7, the gain inclination control unit 20, the  
5 input detecting units 21-1 and 21-2, and the gain control units 24-1 and 24-2. The reference number 1 denotes the input terminal, and 2 denotes the output terminal.

The output detecting unit 5-2 detects an output level of a wavelength-multiplexed signal light at an output side  
10 of the second wavelength selecting unit 18-2, and outputs a detection value to the output control unit 6. The output control unit 6 controls the attenuation of an output signal light attenuated by the optical variable attenuator 4 according to the detection value so that the output level  
15 detected by the output detecting unit 5-2 becomes constant. The gain inclination detecting unit 7 detects a gain inclination from an output of the second wavelength selecting unit 18-2, and outputs a detection value to the gain inclination control unit 20. The gain inclination control  
20 unit 20 controls the gain inclination to an optimum value by adjusting output levels of the first compensation light source 17-1 and the second compensation light source 17-2 according to a gain inclination (a detection value) detected by the gain inclination detecting unit 7.

25 Therefore, in this ninth embodiment also, like in the

first embodiment, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed  
5 signal light.

Tenth Embodiment:

Fig. 14 shows a tenth embodiment of an optical amplifier apparatus according to the present invention.

The optical amplifier apparatus of the tenth  
10 embodiment has the first and second optical amplifiers 3-1 and 3-2, the optical variable attenuator 4, the first and second compensation light sources 17-1 and 17-2, the first and second wavelength selecting units 18-1 and 18-2, the output detecting units 5-1 and 5-2, the output control unit  
15 19, the gain inclination detecting unit 7, the gain inclination control unit 16, the input detecting units 21-1 and 21-2, and the gain control units 24-1 and 24-2. The reference number 1 denotes the input terminal, and 2 denotes the output terminal.

20 The output detecting unit 5-2 detects an output level of a wavelength-multiplexed signal light at an output side of the second wavelength selecting unit 18-2, and outputs a detection value to the output control unit 19. The output control unit 19 controls output levels of the first  
25 compensation light source 17-1 and the second compensation

light source 17-2 according to the detection value so that the output level detected by the output detecting unit 5-2 becomes constant. The gain inclination detecting unit 7 detects a gain inclination from an output of the second wavelength selecting unit 18-2, and outputs a detection value to the gain inclination control unit 16. The gain inclination control unit 16 controls the gain inclination to an optimum value by adjusting the attenuation of an output signal light attenuated by the optical variable attenuator 4 according to a gain inclination (a detection value) detected by the gain inclination detecting unit 7.

Therefore, in this tenth embodiment also, like in the first embodiment, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed signal light.

#### Eleventh Embodiment:

Fig. 15 shows an eleventh embodiment of an optical amplifier apparatus according to the present invention.

The optical amplifier apparatus of the eleventh embodiment has the first and second optical amplifiers 3-1 and 3-2, the first and second compensation light sources 17-1 and 17-2, the first and second wavelength selecting units 18-1 and 18-2, the output detecting units 5-1 and 5-2,

the output control unit 19, the gain inclination detecting unit 7, the gain inclination control unit 23, the input detecting units 21-1 and 21-2, and the gain control units 24-1 and 24-2. The reference number 1 denotes the input terminal, and 2 denotes the output terminal.

The output detecting unit 5-2 detects an output level of a wavelength-multiplexed signal light at an output side of the second wavelength selecting unit 18-2, and outputs a detection value to the output control unit 19. The output control unit 19 controls output levels of the first compensation light source 17-1 and the second compensation light source 17-2 according to the detection value so that the output level detected by the output detecting unit 5-2 becomes constant. The gain inclination detecting unit 7 detects a gain inclination from an output of the second wavelength selecting unit 18-2, and outputs a detection value to the gain inclination control unit 23. The gain inclination control unit 23 controls the gain inclination to an optimum value by adjusting output lights of excitation light sources of the first optical amplifier 3-1 and the second optical amplifier 3-2 according to a gain inclination (a detection value) detected by the gain inclination detecting unit 7.

Therefore, in this eleventh embodiment also, like in the first embodiment, it is possible to realize an optical





5-2 becomes constant. The gain inclination detecting unit 7 detects a gain inclination from an output of the second wavelengthselecting unit 18-2, and outputs a detection value to the gain inclination control unit 20. The gain inclination control unit 20 controls the gain inclination to an optimum value by adjusting output lights of the first compensation light source 17-1 and the second compensation light source 17-2 according to a gain inclination (a detection value) detected by the gain inclination detecting unit 7.

Therefore, in this twelfth embodiment also, like in the first embodiment, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed signal light.

As can be understood from the above explanation, according to one aspect of the present invention, the output control unit controls an output level of the optical amplifier according to an output level detected by the output detecting unit. The gain inclination control unit controls a gain inclination of the optical amplifier according to a gain inclination detected by the gain inclination detecting unit. Therefore, it is possible to realize an optical amplifier apparatus capable of controlling the gain

inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed signal light.

According to another aspect of the invention, the  
5 output control unit controls the attenuation of an output signal light attenuated by the optical variable attenuator according to an output level detected by the output detecting unit. The gain inclination control unit controls a gain inclination by adjusting an output light of an excitation  
10 light source of the optical amplifier according to a gain inclination detected by the gain inclination detecting unit. Therefore, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the  
15 amplification of a wavelength-multiplexed signal light.

According to still another aspect of the invention, the output control unit controls an output light of an excitation light source of the optical amplifier according to an output level detected by the output detecting unit.  
20 The gain inclination control unit controls a gain inclination by adjusting the attenuation of an output signal light attenuated by the optical variable attenuator according to a gain inclination detected by the gain inclination detecting unit. Therefore, it is possible to realize an optical  
25 amplifier apparatus capable of controlling the gain

inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed signal light.

According to still another aspect of the invention,  
5 the output control unit controls an output light of the compensation light source according to an output level detected by the output detecting unit. The gain inclination control unit adjusts an output light of an excitation light source of the optical amplifier according to a gain  
10 inclination detected by the gain inclination detecting unit. Therefore, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed signal light.

15 According to still another aspect of the invention, the output control unit controls an output light of an excitation light source of the optical amplifier according to an output level detected by the output detecting unit. The gain inclination adjusts an output light of the  
20 compensation light source according to a gain inclination detected by the gain inclination detecting unit. Therefore, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of  
25 a wavelength-multiplexed signal light.

According to still another aspect of the invention, the output control unit controls the attenuation of an output signal light of the optical variable attenuator according to an output level detected by the output detecting unit.

5 The gain inclination control unit adjusts an output light of the compensation light source according to a gain inclination detected by the gain inclination detecting unit. Therefore, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the  
10 amplification of a wavelength-multiplexed signal light.

According to still another aspect of the invention, the output control unit controls an output light of the compensation light source according to an output level  
15 detected by the output detecting unit. The gain inclination control unit controls a gain inclination by adjusting the attenuation of an output signal light attenuated by the optical variable attenuator according to a gain inclination detected by the gain inclination detecting unit. Therefore,  
20 it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed signal light.

According to still another aspect of the invention,  
25 the output control unit controls the attenuation of an output

signal light attenuated by the optical variable attenuator according to an output level detected by the output detecting unit. The gain inclination control unit controls a gain inclination by adjusting output lights of excitation light sources of the first optical amplifier and the second optical amplifier according to a gain inclination detected by the gain inclination detecting unit. Therefore, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed signal light.

According to still another aspect of the invention, the output control unit controls output lights of excitation light sources of the first optical amplifier and the second optical amplifier according to an output level detected by the output detecting unit. The gain inclination control unit controls a gain inclination by adjusting the attenuation of an output signal light attenuated by the optical variable attenuator according to a gain inclination detected by the gain inclination detecting unit. Therefore, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed signal light.

According to still another aspect of the invention,

the output control unit controls the attenuation of an output signal light attenuated by the optical variable attenuator according to an output level detected by the output detecting unit. The gain inclination control unit controls a gain inclination by adjusting an output light of the compensation light source according to a gain inclination detected by the gain inclination detecting unit. Therefore, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed signal light.

According to still another aspect of the invention, the output control unit controls an output light of the compensation light source according to an output level detected by the output detecting unit. The gain inclination control unit controls a gain inclination by adjusting the attenuation of an output signal light attenuated by the optical variable attenuator according to a gain inclination detected by the gain inclination detecting unit. Therefore, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed signal light.

According to still another aspect of the invention, the output control unit controls output lights of excitation

light sources of the first optical amplifier and the second optical amplifier according to an output of the output detecting unit. The gain inclination control unit controls a gain inclination by adjusting an output light of the compensation light source according to a gain inclination  
5 detected by the gain inclination detecting unit. Therefore, it is possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of  
10 a wavelength-multiplexed signal light.

According to still another aspect of the invention, the output control unit controls an output light of the compensation light source according to an output level detected by the output detecting unit. The gain inclination  
15 control unit controls a gain inclination by adjusting output lights of an excitation light source of the first optical amplifier and an excitation light source of the second optical amplifier according to a gain inclination detected by the gain inclination detecting unit. Therefore, it is  
20 possible to realize an optical amplifier apparatus capable of controlling the gain inclination as well as making constant the optical output level, in the amplification of a wavelength-multiplexed signal light.

Moreover, the gain inclination detecting unit branches  
25 a wavelength-multiplexed signal light, and detects a gain

inclination from optical signal levels of a shortest wave and a longest wave. Therefore, it is possible to properly detect the gain inclination.

Furthermore, the gain inclination detecting unit  
5 branches a wavelength-multiplexed signal light, and detects a gain inclination from optical signal levels of three or more waves. Therefore, it is possible to properly detect the gain inclination.

Moreover, the gain inclination detecting unit detects  
10 frequency components superimposed on the optical signals of respective wavelengths thereby to detect a gain inclination. Therefore, it is possible to properly detect the gain inclination.

Furthermore, the gain inclination detecting unit  
15 detects frequency components superimposed on the optical signals thereby to detect a gain inclination. Therefore, it is possible to properly detect the gain inclination.

#### INDUSTRIAL APPLICABILITY

20 As explained above, the optical amplifier apparatus according to the present invention is suitable for application to an optical repeater and the like for wavelength multiplex transmission.